



# S600 DVB-S USB Specification

- ➔ High sensitivity CAN tuner DVB-S
- ➔ Bundled Software myTeVii
- ➔ Bonus Trial version of ProgDVB Pro
- ➔ Bundled IP software TeViidata



## Software Key Features

- DVB-S TV and Radio Playback on PC
- Real Time and Pre-Scheduled Recording (PVR)
- Time-Shifting
- HDTV Support (MPEG2)
- Electronic Program Guide (EPG)
- Subtitles
- DiSEqC 1.0/1.1/1.2 & USALS support
- Favorite List
- On Screen Display (OSD)
- Remote control Support
- English/Russian/German/French Multi-languages Support

## Specification

- Tuner Type: Sharp CAN tuner
- Input terminal: F-type 75 Ohm
- Receiving frequency: 950~2150 MHz
- Input level: -70~-20dBm
- Support MCPC and SCPC



# S600 DVB-S USB Specification

## QPSK & FEC

- Symbol rate: 2~45 MS/s
- FEC: 1/2, 2/3, 3/4, 5/6, 7/8 and Auto
- QPSK filter: Root-raised cosine filter with roll-off 0.35

## LNB & Switch control

- LNB Supply Voltage: 13V/18V
- DiSEqC: 1.0, 1.1, 1.2,
- Support Data Burst & Tone Burst
- Antenna & LNB Control: 22KHz
- Max. LNB supply current: 400mA with short circuit & surge protection

## System Requirements

- Microsoft Windows 2000/XP/Vista
- 2.0GHz CPU (2.4GHz for HDTV)
- 256M RAM (1GB for HDTV)
- VGA card with at least 128MB memory
- Sound card or on-board sound chip
- One Free USB 2.0 Port
- Microsoft Direct X 9.0C or above
- Digital Satellite Dish & LNB