



S630 DVB-S USB Specification

- High sensitivity silicon tuner DVB-S
- Bundled software myTeVii
- Trial version of ProgDVB Pro
- Bundled IP software TeViidata



Software Key Features

- DVB-S TV and Radio Playback on PC
- Real Time recording in MPEG/TS format
- Time-Shifting
- HDTV support (MPEG2)
- Electronic Program Guide (EPG)
- Subtitles
- DiSEqC 1.0/1.1/1.2 & USALS support
- Favorite List
- On Screen Display (OSD)
- Remote control Support
- English/Russian/German/French Multi-languages Support

Tuner

- Tuner Type: High Sensitivity Silicon Tuner
- Input terminal: F-type 75 Ohm
- Receiving frequency: 950~2150 MHz
- Input level: -70~-20dBm



S630 DVB-S USB Specification

LNB & Switch control

- LNB Supply Voltage: 13V/18V
- DiSEqC: 1.0, 1.1, 1.2,
- Support Data Burst & Tone Burst
- Antenna & LNB Control: 22KHz
- Max. LNB supply current: 400mA with short circuit & surge protection

USB Interface

- Bus: Universal Serial Bus 2.0 standard
- Mini USB connector

Package Includes

- S630 DVB-S USB box
- Power adapter
- Remote control
- USB cable
- Installation CD
- Quick Installation Guide

System Requirements

- Microsoft Windows 2000/XP/Vista
- 1.8GHz CPU (2.4GHz for HDTV)
- 256M RAM (1GB for HDTV)
- VGA card with at least 32MB memory
- Sound card or on-board sound chip
- One free USB 2.0 port
- Microsoft Direct X 9.0C or above
- Digital satellite Dish & LNB